

### Model 531

# 4-20 Milliamp Loop Calibrator

### **Datasheet**

### **Features**

### 4 to 20 mA Loop Functions

Source and Read 0.000-24.000 mA

Simulate 2-Wire Transmitters 0.000-24.000mA

Power 2-Wire Transmitters and Read 0.000-24.000 mA

Display current in mA or -25.00-125.00 % of 4-20 mA

#### **Full 4 Digit Display**

True ±0.05% of reading accuracy

Bar graph for quick reference of input and output levels

High contrast graphic display viewable in all lighting conditions and angles

#### **EZ-Dial Knob**

Easily adjust output by 00.01 mA (0.01 %) or 0.1 mA (1.00 %)

### **EZ-Check Switch with EZ-Step Button**

3-position tactile switch for true one-handed calibrations

Slide switch for stepping through calibration points

### Uses a standard 9V Alkaline Battery

Superior battery life up to 40 hours under typical continuous usage

Easy access to battery compartment


### 240 VAC Tolerant

Fuse-less protection from accidental misuse

### Lightweight and rugged with a solid feel

#### HART® protocol compatibility mode

User selectable 250 $\Omega$  resistor in series with the output for compatibility with HART® protocol enabled devices.



### **Description**

The Practical Instrument Electronics Model 531 is the result of 30+ years of experience manufacturing and designing calibrators for the process control industry. Almost all of the Fortune 500 manufacturers use calibrators designed by our engineers. The Model 531 calibrator incorporates all of this knowledge and experience and combines it into one small but powerful product. It has simple, easy to use controls featuring a large high contrast display with easy visibility without the need for contrast adjustments. The Model 531 is designed to be a tool with all the practical functions required to get the job done easily without the confusing extras or reading through a complicated manual. The Model 531 can source and read current in the process loop and simulate, power and measure 2-wire transmitters. It fits in your pocket or you can clip in on your belt.



## **Model 531 Datasheet**

### **Specifications**

### **General Specifications:**

(Unless otherwise indicated all specifications are rated from a nominal 23 °C, 70 % RH for 1 year from calibration)

Operating Temperature Range -20 to 60 °C (-5 to 140 °F)

Storage Temperature Range -30 to 60 °C (-22 to 140 °F)

Relative Humidity Range 10 %  $\leq$ RH  $\leq$ 90 % (0 to 35 °C), Non-condensing

10 %  $\leq$ RH $\leq$  70 % (35 to 60 °C), Non-condensing

Size 4.75 X 2.50 X .75 inches (120.65 x 63.5 x 19.05mm)

Weight 7.5 oz (212.6 grams)

Battery 9V Alkaline

Optional 120 VAC 50/60 Hz AC adaptor available

Miscellaneous Low battery indication with nominal 1 hour of operation left

Over-voltage protection to 120 Vrms (rated for 30 seconds)

Bar graph display with 1% resolution of 4-20 mA signal scale

High contrast graphic liquid crystal display with 0.45" (11.4 mm) high digits

#### Common Specifications for all current modes

Ranges 0.000 to 24.000 mA, -25.00 to 125.00% of 4-20 mA Accuracy  $\leq \pm (0.05 \% \text{ of Reading} + 0.004 \text{ mA})$ Temperature effect  $\leq \pm 50 \text{ ppm/°C of Range}$ Resolution(s) 00.01 mA and 0.01 %

### Source/Power and Measure 2-Wire Transmitter Specifications:

Loop compliance voltage  $\geq 24$  Volts

Loop drive capability 1200  $\Omega$  at 20 mA for entire battery life

Miscellaneous Open loop or out of compliance conditions are indicated by appropriate error display

Battery life in:

Source mode  $\geq 18$  hrs at 12mA typical (HART® disabled)

Power measure  $\geq 10$  hrs at 12mA typical

HART® protocol mode places a 250 $\Omega$  resistor in series with the output

### Read mA Specifications:

Voltage burden	≤ 2V at 20 mA
Overload/Current limit protection	24 mA nominal
Battery life	Typical ≥ 40 Hours



# **Model 531 Datasheet**

#### 2-Wire Transmitter Simulation Specifications:

Voltage burden ≤ 2V at 20 mA

Overload/Current limit protection

24 mA nominal

Loop voltage limits

2-60 VDC

Miscellaneous

Open loop or out of compliance conditions are indicated by flashing error on display

Battery life ≥ 40 hour typical

### **Available Options:**

Option:	Part Number:
Carrying Case	020-0200

### Other Products Available:

RTD Source (Single Type/1° resolution)		Model 510
RTD Source (7 Types, Ω/0.1° resolution)		Model 511
	Pt100: a=1.3850, 1.3902, 1.3916, 1.3926	
	Cu10: a=1.427	
	Ni110: a=1.530	
	Ni120: a=1.672	
	RTD Calibrator (Source/Read 7 Types, $\Omega$ /0.1° resolution)	Model 512
	RTD Calibrator (Source/Road & Types O /0.10 resolution)	Model 5129

RTD Calibrator (Source/Read 7 Types,  $\Omega$  /0.1° resolution)

With Auto Stepping

T/C Source (Single Type/1° resolution)

Model 520

T/C Source (8 Types, mV/0.1° resolution) Model 521

B, E, J, K, N, R, S, T, mV

T/C Calibrator (Source/Read 8 Types, mV/0.1° resolution) Model 522

 $\mathsf{B},\,\mathsf{E},\,\mathsf{J},\,\mathsf{K},\,\mathsf{N},\,\mathsf{R},\,\mathsf{S},\,\mathsf{T},\,\mathsf{mV}$ 

Dual RTD - T/C Source and Read Model 525
4-20 Milliamp Loop Calibrator Model 530
4-20 Milliamp Loop Calibrator with Loop Diagnostic Model 532
4-20/10-50 Dual Range Loop Calibrator Model 535



# **Model 531 Datasheet**

### Warranty

Our equipment is guaranteed against defective material and workmanship (excluding batteries) for a period of three years from the date of shipment. Claims under guarantee can be made by returning the equipment prepaid to our factory. The equipment will be repaired, replaced or adjusted at our option. The liability of Practical Instrument Electronics (PIE) is restricted to that given under our guarantee. No responsibility is accepted for damage, loss or other expense incurred through sale or use of our equipment. Under no condition shall Practical Instrument Electronics, Inc. be liable for any special, incidental or consequential damage.

### **Your Local PIE Representative**

# TM Solutions inc.

www.tmsolution.co.kr Ph: +82-2-837-2526